



T03 Line Sequence Converter

T03 Line Sequence Converter is plug-and-play and easy to deploy.

Fanvil IP Phone can support 03 line sequence headset by this accessory,, greatly improving the adaptability and flexibility.

Highlights

- ☑ Compatible with Fanvil IP Phone
- ☑ Ease-of-use
- ☑ Plug and Play




Product Specifications

- Cable length: 150mm \pm 30mm
- Line sequence: From Q01 to Q03
- Interface: RJ9 Socket (4P4C) and RJ9 Plug (4P4C)
- Working temperature: 0~45℃
- Working humidity: 20~85%
- Color: Black


Packaging information

- Packing bag dimensions: 100 x 150 mm
- N.W/PCS: 7.6 g
- G.W/PCS: 10 g

Q03 line sequence (RJ9 Socket)



Q01 Line sequence (RJ9 Plug)



Q03 Line sequence (RJ9 Socket)

1. MIC+
2. Speaker-
3. Speaker+
4. MIC-

Q01 Line sequence (RJ9 Plug)

1. MIC-
2. Speaker-
3. Speaker+
4. MIC+

The above specifications may be updated in the future without prior notice. All hardware/software/physical features should be based on the final shipped products.
For more information, please visit: www.fanvil.com

